



**GaN Charger
GM3A / GM3C
Instruction Manual**



a



b



**Read the instruction manual thoroughly before use.
Keep the manual for future reference.**

GB

Using Your Product

1. Attach the plug to the charger by sliding the plug onto the pins until you hear a "click" sound. (See figure a)
* Ensure to slide the top pin of the UK plug into its extended position before plugging the charger into a power outlet.
(See figure b)
2. Plug the charger into a power outlet.
3. Connect your devices to the USB ports with the included USB-C cable or another certified cable. The charger can charge up to 3 devices at the same time. To charge at more than 60W, you must use the included cable or another USB-C E-Mark cable.
(See figure c)

Specifications

Input : AC 100-240V, 50/60Hz, 1.5A Max.

Output : Single port charging
USB-C1/C2 – DC 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3.25A, 65W Max.
USB-A – DC 4.5V/5A, 5V/4.5A, 9V/3A, 12V/2.5A, 20V/1.5A, 30W Max.
Simultaneous charging
USB-C1+USB-C2 – 45W+18W, 63W Max.
USB-C1+USB-A – 45W+18W, 63W Max.
(USB-A/C2 – DC 5V/3A, 9V/2A, 12V/1.5A)
USB-C2+USB-A – DC 5V/3A, 15W Max.
USB-C1+USB-C2+USB-A – 45W+15W, 60W Max.

Total Output : 65W Max.

Dimensions* : 67(L) x 42(W) x 31(H)mm

Weight* : 113g

*Excluding plugs

Safety information



Please read below safety notes carefully before use to avoid any personal injury and property damage caused by improper use of the product. Any warranty claims or returns caused by misuses will not be accepted.

- Keep the product away from children and infirm persons.
- Keep the product away from heat sources, combustible gas, humidity and liquids.
- Do not operate a wet or otherwise damaged product.
- Operating temperature should be between 0°C to 25°C.
- Be careful not to crash the product while it is plugged in to avoid damage.
- Do not attempt to repair, disassemble or destroy the product in any way.
- Keep the product away from metallic or conductive objects to avoid short-circuit.
- Dispose the product as per local law and regulations.

GaN Charger GM3A / GM3C Instruction Manual

GP

210581_GM3C_IB_V1_01



Read the instruction manual thoroughly before use.
Keep the manual for future reference.

GB

Using Your Product

1. Attach the plug to the charger by sliding the plug onto the pins until you hear a "click" sound. (See figure a)
* Ensure to slide the top pin of the UK plug into its extended position before plugging the charger into a power outlet. (See figure b)
2. Plug the charger into a power outlet.
3. Connect your devices to the USB ports with the included USB-C cable or another certified cable. The charger can charge up to 3 devices at the same time. To charge at more than 60W, you must use the included cable or another USB-C E-Mark cable. (See figure c)

Specifications

Input : AC 100-240V, 50/60Hz, 1.5A Max.
Output : Single port charging
USB-C1/C2 – DC 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3.25A, 65W Max.
USB-A – DC 4.5V/5A, 5V/4.5A, 9V/3A, 12V/2.5A, 20V/1.5A, 30W Max.
Simultaneous charging
USB-C1+USB-C2 – 45W+18W, 63W Max.
USB-C1+USB-A – 45W+18W, 63W Max.
(USB-A/C2 – DC 5V/3A, 9V/2A, 12V/1.5A)
USB-C2+USB-A – DC 5V/3A, 15W Max.
USB-C1+USB-C2+USB-A – 45W+15W, 60W Max.

Total Output : 65W Max.

Dimensions* : 67(L) x 42(W) x 31(H)mm

Weight* : 113g

*Excluding plugs

Safety Information

Please read below safety notes carefully before use to avoid any personal injury and property damage caused by improper use of the product. Any warranty claims or returns caused by misuses will not be accepted.

- Keep the product away from children and infirm persons.
- Keep the product away from heat sources, combustible gas, humidity and liquids.
- Do not operate a wet or otherwise damaged product.
- Operating temperature should be between 0°C to 25°C.
- Be careful not to crash the product while it is plugged in to avoid damage.
- Do not attempt to repair, disassemble or destroy the product in any way.
- Keep the product away from metallic or conductive objects to avoid short-circuit.
- Dispose the product as per local law and regulations.